

PRODUCT OVERVIEW

The latest model of Emergency Lighting Luminaire ,LD-111, is a revolutionary product of its kind. With the combination of High power/ High Lumen LED , microcontroller and Intelligent Battery Charger, users can reap numerous benefits from using our superior product as follow :

- Gain 4 times more efficiency than those conventional emergency lighting luminaires that used Halogen lamps.
- Service life of LED is 25 times longer than that of Halogen lamp.
- Reduce battery size down by 60 %
- System test function can be activated by IR remote controller
- Suitable for contemporary interior design


MODEL : LD - 111

FEATURES

- Extruded aluminum case with the thickness of 1.6mm ,coated with powder paint.
- Brightness is comparable to two of 35 watts Halogen lamp
- Powered by sealed lead-acid battery, size 7.5 AH / 12 VDC
- Relatively constant light output regardless of battery voltage level
- Pilot lamps display system status
- Programmed auto-self test / discharge : 10 seconds every week 1 hour every 4 weeks
- Industrial Standard : TIS-1955-2551
- System warrantee : 5 years , Battery warrantee : 2 year

SPECIFICATION

INPUT VOLTAGE :	220 V./50 Hz.
LAMP POWER :	9 W. x 2
COLOR TEMP.	2,700 - 3,500 K
LAMP CURRENT :	700 mA.
SEALED LEAD ACID BATTERY :	12 VOLT 7.5 AH.
MAX. CHARGER CURRENT :	750 mA
BATT. BOOST / FLOAT VOLTAGE :	14.5 V. / 13.5 V.
BATT.CUTOFF VOLTAGE :	10.5V.
MAX. BACKUP TIME :	4 Hr.
CHARGING TIME :	10 Hr.
DIMENSION :	218 x 283 x 83 mm
WEIGHT :	4 KG.



DIMENSION



TIS.1955-2551