



Figure. A



Figure. B



Figure. C

HP Series

MODEL	FOR LAMP (Max. Load)			BATTERY	DIMENSION L x W x H (cm.)	DURATION (Hrs.-Mins.)	WEIGHT (kgs.)	FIGURE
	Flament	Electronic Ballast	Magnetic Ballast					
HP 200	200W.	200W.	108W.	12V. 28Ah.x 2 : 24V 28Ah.	40 x 40 x 57	2.00	47	A
HP 400	400W.	400W.	180W.	12V. 55Ah.x 2 : 24V 55Ah.			63	
HP 500	500W.	500W.	250W.	12V. 65Ah.x 2 : 24V 65Ah.			75	
HP 700	700W.	700W.	360W.	12V. 80Ah.x 2 : 24V 80Ah.			80	
HP 1000	1000W.	1000W.	540W.	12V. 65Ah.x 4 : 48V 65Ah.	40 x 60 x 100	2.00	160	B
HP 1500	1500W.	1500W.	720W.	12V. 90Ah.x 4 : 48V 90Ah.			190	
HP 2000	2000W.	2000W.	1080W.	12V. 120Ah.x 4 : 48V 120Ah.			225	
HP 3000	3000W.	3000W.	1440W.	12V. 180Ah.x 4 : 48V 180Ah.			350	
HP 3700	3700W.	3700W.	1800W.	12V. 120Ah.x 8 : 96V 120Ah.	50 x 65 x 165	2.00	420	C
HP 4500	4500W.	4500W.	2150W.	12V. 134Ah.x 8 : 96V 134Ah.			440	